



[www.bombaycompany.com](http://www.bombaycompany.com)

**5017564**

**Brittany Chandelier**

**Parts and Hardware List**

A.	Chandelier Assembly	1 pc
B.	Small Crystals	2 pcs
C.	Big Crystal	1 pc
D.	Mounting Strap	1 pc
E.	Mounting Screws	2 pcs
F.	Pre-Threaded Pipe	1 pc
G.	Hex Nut	1 pc
H.	Collar	1 pc
I.	Pre-Threaded Ring	1 pc
J.	Canopy	1 pc
K.	Wire Connectors	2 pcs

- Please make sure that you have all the parts indicated before you begin assembly of this item.

**Please read Wiring Instructions before you begin assembling and installing your Chandelier.**

**Attach Mounting Strap to Outlet Box**

1. Carefully remove the parts and hardware from the carton.
2. Fasten the Mounting Strap (D) to the outlet box using the Mounting Screws (E).
3. Insert the shorter end of the Pre-Threaded Pipe (F) into the pre-drilled hole in the Mounting Strap (D) and secure with the Hex Nut (G). See Illustration.
4. Attach the Collar (H) to the exposed end of the Pre-Threaded Pipe (F) and secure by turning in a clockwise direction.
5. Attach one end link of the Chain to the loop on the top of the Chandelier Assembly (A).
6. Slip the Pre-Threaded Ring (I) first and then the Canopy (J) over the other end of the chain. Attach the open link on this end of the chain to the Collar (H).
7. Lace the wire through every other link of the chain, through the collar and up through the Pre-Threaded Pipe (F). See Illustration.
8. Hang Crystals (B & C) on Chandelier Assembly (A) as shown in Illustration.
9. Install 25 Watt, Type B bulbs (sold separately) into the sockets of the fixture.



**5017564**

## **Brittany Chandelier**

**CLEANING:** This item has a lacquered and baked finish. When cleaning only use a soft, dry cloth. Do not use liquid abrasives as they may discolor the finish.

### **WIRING INSTRUCTIONS**

**CAUTION: THE FOLLOWING INSTRUCTIONS MUST BE FOLLOWED TO ENSURE YOUR SAFETY WHEN INSTALLING THE CHANDELIER FIXTURE.**

**If you are unsure how to install a light fixture or if the fixture fails to work properly contact a qualified electrician.**

1. Power at the fuse box should be disconnected before installing the fixture.
2. The fixture ground wire (bare wire) is not to be connected to any current carrying supply wires.
3. Ensure there are no bare wires exposed outside the wire connectors when joining current carrying wires.
4. Be sure the insulation on the wires has not been damaged during installation.
5. No rough or sharp edges should come in contact with any of the wires.
6. Check to be sure fixture wires are connected to the proper house supply wires. If you have any doubts about which house supplier wire is white and which is black contact a qualified electrician before you continue installation.
7. Do not install light bulbs with higher wattage than what is specified for this fixture.
8. Turn power off when installing light bulbs into the fixture.

### **Connecting the Wires-See Illustrations for reference**

1. Place the white, ribbed or tinted wire from the fixture evenly against the white wire from the outlet box.
2. Fit the wire connector over the ends of the two wires and turn the connector clockwise until it is firmly attached.
3. Gently pull on the connector. If you can pull the connector off, carefully repeat steps 1 & 2 and check again to ensure connector is firmly attached.
4. Connect the black, smooth or un-tinted wire from the fixture to the black wire from the outlet box in the same manner described above in steps 1 through 3.
5. If your outlet box provides a grounding wire (green or bare copper only), attach the wire and the bare copper wire from the fixture to the green grounding screw by wrapping both wires under the head of the screw and tightening screw in a clockwise direction. If the outlet box does not provide a grounding wire, attach the bare copper wire from the fixture to the green grounding screw.

**WARNING: DO NOT ATTACH ANY OTHER WIRES BESIDES THE GREEN OR BARE COPPER WIRE TO THE GROUNDING SCREW.**

6. **After the wires are connected, tuck them carefully inside the outlet box. Place Canopy (J) over the outlet box**



[www.bombaycompany.com](http://www.bombaycompany.com)

**5017564**

**Brittany Chandelier**

and secure with Collar (H).



[www.bombaycompany.com](http://www.bombaycompany.com)

**5017564**

**Brittany Chandelier**

Illustrations will go on this page...